

Amendment/Reply

Applicant: Jenoe Tihanyi

Serial No.: 10/806,958

Filing Date: March 23, 2004

Docket: 1434.105.101/IFT976US

Title: LATERAL FIELD-EFFECT-CONTROLLABLE SEMICONDUCTOR COMPONENT FOR RF APPLICATIONS

IN THE CLAIMS

Please amend claims 1 and 13 as follows:

1. (Currently Amended) A semiconductor component comprising:
a semiconductor body with a first semiconductor layer of a first conduction type and a second semiconductor layer of a second conduction type, which is applied on the first semiconductor layer and forms a front side of the semiconductor body;
in the second semiconductor layer, a first terminal zone of the second conduction type, a drift zone of the second conduction type, a channel zone of the first conduction type, which is formed between the first terminal zone and the drift zone, and a second terminal zone of the second conduction type, which is arranged at a distance from the channel zone in a lateral direction of the semiconductor body;
a gate electrode arranged in a manner insulated from the semiconductor body and adjacent to the channel zone; and
a plurality of auxiliary electrodes arranged at a distance from one another and formed in pillar-type fashion such that each has relatively similar dimensions in the lateral direction;
wherein at least one of the plurality of auxiliary electrodes, which, proceeding from the front side, extends through the second semiconductor layer right into the first semiconductor layer and which is insulated from the semiconductor body.
2. (Cancelled)
3. (Cancelled)
4. (Previously Presented) The semiconductor component of claim 2, wherein the plurality of auxiliary electrodes are completely surrounded by an insulation layer in the semiconductor body.

Amendment/Reply

Applicant: Jenoe Tihanyi

Serial No.: 10/806,958

Filing Date: March 23, 2004

Docket: I434.105.101/IFT976US

Title: LATERAL FIELD-EFFECT-CONTROLLABLE SEMICONDUCTOR COMPONENT FOR RF APPLICATIONS

5. (Previously Presented) The semiconductor component of claim 2, wherein the plurality of auxiliary electrodes are connected to a defined potential.
6. (Previously Presented) The semiconductor component of claim 5, wherein the plurality of auxiliary electrodes and the first terminal zone are connected to the same potential.
7. (Previously Presented) The semiconductor component of claim 1, wherein the gate electrode is arranged above the front side of the semiconductor body.
8. (Previously Presented) The semiconductor component of claim 1, wherein the gate electrode is arranged in the semiconductor body.
9. (Original) The semiconductor component of claim 1, wherein the first semiconductor layer has a more heavily doped semiconductor layer of the first conduction type at a side remote from the second semiconductor layer.
10. (Previously Presented) The semiconductor component of claim 1, wherein at least one semiconductor zone of the first conduction type is arranged in the drift zone adjacent to the at least one auxiliary electrode.
11. (Original) The semiconductor component of claim 10, wherein the at least one semiconductor zone is arranged in the region of the front side of the semiconductor body.
12. (Previously Presented) The semiconductor component of claim 1, wherein the at least one auxiliary electrode is arranged nearer to the channel zone than to the second terminal zone.
13. (Currently Amended) A semiconductor component comprising:

Amendment/Reply

Applicant: Jenoe Tihanyi

Serial No.: 10/806,958

Filing Date: March 23, 2004

Docket: I434.105.101/IFT976US

Title: LATERAL FIELD-EFFECT-CONTROLLABLE SEMICONDUCTOR COMPONENT FOR RF APPLICATIONS

a semiconductor body having a first layer of a first conduction type and a second layer of a second conduction type, the second layer applied onto the first layer thereby forming a front side of the semiconductor body;

a first terminal zone of the second conduction type in the second layer;

a drift zone of the second conduction type in the second layer;

a channel zone of the first conduction type formed between the first terminal zone and the drift zone;

a second terminal zone of the second conduction type, wherein the second terminal zone and the channel zone are separated by a distance in a lateral direction on the front side of the semiconductor body;

a gate electrode insulated from the semiconductor body and adjacent the channel zone;
and

a plurality of auxiliary electrodes arranged at a distance from one another and formed in pillar-type fashion having relatively similar dimensions in the lateral direction;

wherein at least one auxiliary electrode extending from the front side through the second layer into the first layer and insulated from the semiconductor body.

14. (Cancelled)

15. (Cancelled)

16. (Previously Presented) The semiconductor component of claim 14, wherein the plurality of auxiliary electrodes are completely surrounded by an insulation layer in the semiconductor body.

17. (Previously Presented) The semiconductor component of claim 14, wherein the plurality of auxiliary electrodes are connected to a defined potential.

Amendment/Reply

Applicant: Jenoe Tihanyi

Serial No.: 10/806,958

Filing Date: March 23, 2004

Docket: I434.105.101/IFT976US

Title: LATERAL FIELD-EFFECT-CONTROLLABLE SEMICONDUCTOR COMPONENT FOR RF APPLICATIONS

18. (Previously Presented) The semiconductor component of claim 17, wherein the plurality of auxiliary electrodes and the first terminal zone are connected to the same potential.
19. (Previously Presented) The semiconductor component of claim 13, wherein the gate electrode is arranged in the semiconductor body.
20. (Original) The semiconductor component of claim 13, wherein the first semiconductor layer has a more heavily doped semiconductor layer of the first conduction type at a side remote from the second semiconductor layer.